

Software Information Sheet



JCM American Corporation
JCM Europe GmbH
JCM Gold (H.K.) Ltd.
J-Cash Machine (Thailand) Co., Ltd
Japan Cash Machine Co., Ltd. (Headquarters – Japan)

TEL +1-702-651-0000
TEL +49-211-530645-0
TEL +852-2429-7187
TEL +66-2712-3155-6
TEL +81-6-6703-8405

General Information

Model Name:	EBA-30/34-SD3				SW.Reg. No.	C14-0149-01		G14-081	
SW. Name:	EBA-30(CZE-X)-SD3 ID-003				Date: (mm,dd,yyyy)	02.19.2014		Rev:	A1
SW. Version:	V5.10-07				Note:				
Country (Code):	Czech Republic (CZE)				Guide:				
Currency:	Korun				Check Sum:	2C91			
Direction:	4Way				CRC (seed= 0000):	A665			
Denomination:	Denomi.	Printed	Issued	MRI#	Denomi.	Printed	Issued	MRI#	
Years & MRI Ident 79 th	100	'93		CZK100.1	1000	'96	'93	CZK1000.1B	
	100	'95		CZK100.1B	1000	'08	'08	CZK1000.1C	
	100	'97		CZK100.1C	2000	'96		CZK2000.1A	
	200	'93		CZK200.1	2000	'99		CZK2000.1B	
	200	'96		CZK200.1B	2000	'07		CZK2000.1C	
	200	'98		CZK200.1C	5000	'99	'99	CZK5000.1B	
	500	'95		CZK500.1B	5000	'09			
	500	'97		CZK500.1C					
	500	'09	'09	CZK500.1D					
Acceptance Rate:	No less than 90%								
EPROM:	8 Mbit, 100 ns data access, or faster. ST Part M27C801-100F1 or equivalent								
Modifications:	V5.04-05 → V5.10-07								
Validation:	1. Remove Mag pattern check								
Operation:									
Interface:	2. Support serial number reading command 3. Support baud rate change when downloading via command 4. Improved secret number calculation								
Memo:	<ul style="list-style-type: none"> - The 5,000 Korun notes acceptance will be disabled automatically when the SD3 operation is selected as their length is out of specification for the operation with the stacker. - The length of the 2,000 Korun notes is also out of specification for the operation with the stacker, so JCM will not be responsible for any damages caused by them during the SD3 operation. 								

Dip Switch Settings

#	Dip Switch 1		Dip Switch 2
1	OFF	Setting Off	Without SD3 operation
	ON	Setting Off	SD3 operation (Not accept 5000 Korun)
2	OFF	Setting Off	Disable optional key switch
	ON	Setting Off	Enable optional key switch
3	OFF	100 ACCEPT	Setting Off
	ON	100 INHIBIT	Setting Off
4	OFF	200 ACCEPT	Setting Off
	ON	200 INHIBIT	Setting Off
5	OFF	500 ACCEPT	Without double paper payout detection
	ON	500 INHIBIT	With double paper payout detection
6	OFF	1000 ACCEPT	Setting Off
	ON	1000 INHIBIT	Setting Off
7	OFF	2000 ACCEPT	Setting Off
	ON	2000 INHIBIT	Setting Off
8	OFF	5000 ACCEPT	Setting Off
	ON	5000 INHIBIT	Setting Off

ID-003 Data Setting specification

VERSION DATA

SW. Version	E(CZE-X)-30-SD3 ID003-05v510-07 18FEB14 A665
-------------	--

ESCROW DATA

Code	Denomination
61h	Reserved
62h	Reserved
63h	Reserved
64h	100
65h	200
66h	500
67h	1000
68h	2000
69h	5000

CURRENCY ASSIGN DATA

Code	Country	Denomi	Exp.
61h	00h	00h	00h
62h	00h	00h	00h
63h	00h	00h	00h
64h	2Ch	0Ah	01h
65h	2Ch	14h	01h
66h	2Ch	32h	01h
67h	2Ch	64h	01h
68h	2Ch	C8h	01h
69h	2Ch	32h	02h

ENABLE/DISABLE DATA

DATA bit	Data 1	Data 2
0	Reserved	5000
1	Reserved	Reserved
2	Reserved	Reserved
3	100	Reserved
4	200	Reserved
5	500	Reserved
6	1000	Reserved
7	2000	Reserved

0: Enable 1: Disable (Default: **07FEh**)

SECURITY DATA

DATA bit	Data 1	Data 2
0	Reserved	5000
1	Reserved	Reserved
2	Reserved	Reserved
3	100	Reserved
4	200	Reserved
5	500	Reserved
6	1000	Reserved
7	2000	Reserved

0: Normal 1: Security Level high (Default: **0000h**)

DIRECTION DATA

DATA bit	Direction	Sample: 100 Korun	
0	'A' Direction	A	B
1	'B' Direction		
2	'C' Direction		
3	'D' Direction		
4	Not used	C	D
5	Not used		
6	Not used		
7	Not used		

0: Not Inhibit 1: Inhibit (Default: **00h**)

OPTIONAL FUNCTION DATA

DATA bit	Data 1	Data 2
0	Hanging Function[01]	Not use
1	Power Recovery [02]	Not use
2	Not use	Not use
3	Not use	Not use
4	Not use	Not use
5	Not use	Not use
6	Not use	Not use
7	Encryption [80]	Not use

0: Disable 1: Enable (Default: **0000h**)

[01] Hanging Function

Rejection of the bill is completed with the end of the bill kept remaining in the acceptor.
(To prevent dropping of the bill)

[02] POWER RECOVERY

Limited to the case where power up status is [POWER UP WITH BILL IN STACKER]
with power supply off while ACCEPTOR is in [STACKING] status, [VEND VALID] is
outputted in case initializing is completed normally.

Since SETTING STATUS becomes DEFAULT 0000H by power supply off, it is necessary to
conduct setting without fail after [RESET] command is transmitted.

Remarks

(1) SECURITY DATA

This function is not enabled even if each denomination is set to “Security level high”.

(2) Operation with SD3 stacker: Output timing of [VEND VALID]

When [STACK-1] or [STACK-2] is received, EBA-3x-SD3 will send [VEND VALID] in the following timings:

- * Output timing of [VEND VALID] upon receiving [STACK-1]
EBA-3x-SD3 will send [VEND VALID] after PB unit finishes its operation.
- * Output timing of [VEND VALID] upon receiving [STACK-2]
EBA-3x-SD3 will send [VEND VALID] when a bill is stacked into the cash box.

(3) Operation without SD3 stacker: Output timing of [VEND VALID]

EBA-3x will send [VEND VALID] at the timing of [STACK-1], regardless of receiving [STACK-1] or [STACK-2].

(4) Power recovery

Memory backup period for sec power outage is 5 seconds at minimum. For outage of more than 5 seconds, power recovery becomes impossible and the data in memory will be lost.

(5) The following “FAILURE” and “ERROR” status are added on the communication specification for ID-003 4 th edition.

*FAILURE Status

FAILURE [0x49] + DATA

DATA	Description
0xa1	Stacking mechanism failure
0xb6	Wrong download file
0xc1	Centering mechanism failure
0xc2	The rollers for centering mechanism do not move up and down
0xc3	Communication error with the stacker board

*ERROR Status

[0x4d] Key Unlocked

EBA-3x-SD3 will send this command when the cash box key is unlocked.

EBA-3x-SD3 will initialize itself when the cash box is put into place and the key is locked.

(The key switch is an optional part. EBA-3x-SD3 does not send the error status if the key switch is disabled with dipswitch settings. Bill acceptor does not send this command in operation without SD3 stacker.)

[0x4e] Stacker unit separated form acceptor unit

EBA-3x-SD3 will send this command when the stacker unit separated form acceptor unit.

EBA-3x-SD3 will initialize itself when the stacker unit is put into place.

(EBA-3x-SD3 does not send this command in operation without SD3 stacker)